



Thank you for purchasing the **ZEB-EnergiPod 10R2** Power bank. Please read this user manual carefully before operation and save it for future reference.

#### Note:

- Avoid the usage of this product at high temperature and high humidity environments.
- Avoid the self-disassembling of the product or it will result in voiding the Product's warranty.
- Please charge the product with a power adapter output rated Type-C (Please refer to the specification).

**Caution:** There is a risk of explosion if the product is disposed in the fire.

To know more about Terms and conditions for warranty policy, please visit

https://zebronics.com/pages/warranty-policy

### Features:

22.5W Max Output
Rapid Charging
LED Percentage Display
Mobile/Tablet Compatible
Type-C Input & Output Port
Over Charge Protection
Overload Protection
Short Circuit Protection
Attached Output Cables

### Specifications:

Battery Capacity : 10000mAh

No. of Inputs : 2 No. of Outputs : 5

Inputs

Type-C Port : DC 5V/3A, 9V/2A,

12V/1.5A

USB Cable : DC 5V/2A

Outputs

USB Port : DC 5V/3A, 9V/2A,

12V/1.85A

Type-C Port : DC 5V/3A, 9V/2.2A, 12V/1.67A

Type-C Cable : DC 5V/3A, 9V/2A,

12V/1.85A

Micro USB Cable : DC 5V/2.4A

Lightning Cable : DC 5V/2.4A

(22.5W Max. Output)

Charging Time : 3h, 26Mins. Approx. Product Dimension : 6.7 x 2.1 x 14.8 cm

 $(W \times D \times H)$ 


Net Weight : 233g

# Package Contents:

Power Bank : 1 U Charging Cable : 1 U


QR Code Guide : 1 U

## **Port Descriptions:**




### **Charging Instructions:**

• Connect the Type C end of the charging cable to the power bank and the USB end to the charger or can charge through Built in USB cable.



### Charging your Device with the Power Bank:

 Connect the Type-C / Micro USB / Lightning end of the charging cable to the device and the USB / Type-C end to the output ports of the power bank.



**Note:** Simultaneous Usage of the power bank output provides standard 5VDC output.

ISO 9001:2015 Certified Company www.zebronics.com