



Wireless Headphone

**ZEB** **SILENCIO 111**



**User Manual**

[www.zebronics.com](http://www.zebronics.com)

Dear Customer,

Thank you for purchasing **ZEB-SILENCIO 111** BT headphone. Please read this user manual carefully before operation & save this user manual for further reference

**Note:**

- *Avoid the use of this product at the high temperature and high humidity environment.*
- *Avoid the self-disassembly of the products or it results in voiding the product's Warranty.*
- *Please charge the product with power adapter output rated voltages DC 5V.*

To know more about Terms and conditions for warranty policy, please visit

<https://zebronics.com/pages/warranty-policy>

**Caution:**

Listening at High volumes can cause hearing impairment. Please limit your usage at high volumes

**Features**

40mm Titanium Drivers

Hybrid Active Noise Cancellation (ANC)

Up to 55h\* backup

Rapid Charging (10min charge for 8h\* use)

Transparency Mode

Gaming Mode (Low Latency)

3 EQ Modes

Environmental Noise Cancellation (ENC)

Dual Pairing

Call function

BT v5.4 | AUX

Voice Assistant Support

Soft & Comfortable Earcushion

Built-in Rechargeable Battery

Adjustable Headband

### Specification

Model	: ZEB-DUKE 3
BT version	: v5.4
Wireless Range	: 10 meters (Without obstacles)
Driver Size	: 40mm
Speaker Impedance	: 30Ω
Noise Cancellation	: 35dB
Frequency Response	: 20Hz - 20kHz
Sensitivity	: 109±3dB
Charging Time	: 1.5h
Playback time	
ANC OFF	: 55h*
ANC ON	: 33h*
Standby time	: 400 h
Talk time	: 42h*
Microphone Impedance	: 2.2kΩ
Microphone Sensitivity	: -38±3db
Net. Weight	: 235g

*\*at 50% Volume (ANC OFF)*

## Package Contents

Headphones	: 1 U
Aux cable	: 1 U
Charging cable	: 1 U
QR code guide	: 1 U

## Product Representation



## Button & Port Description:

Button Controls:

- Long Press "Play/Pause" button to Power ON/OFF.
- Single press "+" button: Increase Volume
- Single press "-" button: Decrease Volume
- Single press "Play/Pause" button to Answer/Hang up the phone call
- Long press "+" button for Next Track
- Long press "-" button for Previous Track

- **Triple Press** "Play/Pause" until you hear a single beep to activate Voice Assistant function
- Double press "Play/Pause" button to switch between the Gaming mode/Music Mode.
- Long press the "MFB" button to switch between the EQ mode.
- \* Long Press "Play/Pause" button to Reject the call.
- Single Press "MFB" button to switch between ANC and Transparency mode.

### **Bluetooth Mode:**

- The headphone enters BT mode as soon as it is powered ON. (Refer LED indication and make sure aux is not connected already)
- Now search for nearby BT devices in your audio source device.
- Tap on the BT name "**ZEB-SILENCIO 111**" to pair.

### **Gaming Mode(Low Latency):**

Double press the **Play/Pause** to enable gaming mode and repeat the process to enter into music mode.

### **Dual Paring Mode:**

- Pair the headphone with one device and do not unpair, now turn off the BT on the first device and pair the headphone with the second device.

Now you can turn on the first device and the headphone will automatically pair with the first device (if your device is compatible) else tap on **ZEB-SILENCIO 111** in the BT settings on your first device.

### **Voice Assistant support:**

- When the headphone is connected with a smart phone, Triple press the **Play/Pause** button for 2 seconds to activate the phone's voice assistant function.

### **AUX Mode:**

- Connect one end of the 3.5mm Aux cable to the headphone and connect the other end to any compatible audio source. (Example: Mobile, Tablet, Laptop or Desktop Computer etc)
- Media controls can be done via the audio source device. (Make sure to power on the headphone to use BT mode after removing the aux cable)

### **LED Indication:**

- Charging-Constant Red LED glows
- Full Charge - Red LED goes OFF
- Bluetooth Discover Mode - Blue and Red LED blinks rapidly
- Bluetooth Connected - Constant Blue LED, then LED goes off

**ISO 9001:2015 Certified Company**  
**[www.zebronics.com](http://www.zebronics.com)**

