

4.1 Speaker CUBE 5



User Manual

www.zebronics.com

Thank you for purchasing Zebronics Speaker. Please read this user manual carefully before operation & save it for future reference.

Note:

- Avoid the use of this speaker at the hightemperature and high humidity environment.
- Avoid self-disassemble of speaker, or it will result in the failure of warranty.

Features

4.1 Channel speaker Wireless BT/USB/FM/AUX LED Display 16.51 cm Subwoofer Remote control LED Lights Stylish design

Specification

Output power (RMS)

Subwoofer : 40 Watts
Satellite : 15 Watts x 4
Total : 100 Watts

Driver size

Subwoofer : 16.51 cm Satellite : 7.62 cm x 4

Impedance

Subwoofer :8 Ω Satellite :4 Ω

Frequency response : 40Hz - 20kHz

S/N Ratio :≥72dB Separation :≥45dB File format support (USB) : MP3 Line input : 2ch RCA

Max. supported

memory size (USB) :32GB

FM frequency range : 87MHz-108 Mhz BT name : 7FBRONICS

BT version : 5.1

Product dimension $(W \times D \times H)$

Subwoofer :254 x 335 x 273 mm Satellite :102 x 92 x 165 mm


Net. weight

Subwoofer :5.47 kg Satellite :498g x 4 Total :7.73 kg


Package content

Subwoofer :1 unit
Satellite :4 units
Remote control :1 unit
Input cable :1 unit

Control description



Remote control



General instruction

Bluetooth connectivity

Switch the Speaker to BT mode, Scan for nearby BT devices in your mobile. Tap on "ZEBRONICS" to connect.

USB Mode

Insert the USB pen drive card to the speaker. The speaker will detect the USB & audio from it will be played automatically.

FM Radio

Switch the speaker to FM mode. In FM Mode, long press the Play / Pause key to scan the available FM channels. Once the scanning is done, the speaker will start playing the first scanned channel. The next and Prev. buttons can be used to change the FM channels.

AUX-IN

The speaker can be connected to an audio device using an RCA to 3.5mm cable. Connect the one end of the cable to the speaker & connect the other end of the cable to an audio source. The songs from the audio source can be heard through the speaker.

ISO 9001:2015 Certified Company www.zebronics.com