

m2.0 Bookshelf Speaker HBT4848 RUCF



User Manual

www.zebronics.com

Thank you for purchasing the **ZEB-BT4848RUCF** 2.0 Bookshelf speaker. Please read the user manual before usage and save it for future reference.

Note:

- Avoid the usage of this speaker at the high temperature and high humidity environment.
- Avoid the self-disassembly of the product or it results in voiding the product's warranty.
- Turn off the speaker when the speaker is not in use.
- To know more about Terms and conditions for warranty policy,

https://zebronics.com/pages/warranty-policy

Features:

BT v5.0 / AUX / FM Radio / USB 2.0 Channel Book Shelf 2-Way Speaker Headphone Output Media / Volume Controls LED Display Remote Control LED Light

Specification:

Output Power (RMS) : 80W (40W + 40W)
Driver Size : Woofer - 11.8cm x 2

: Tweeter - 5.08cm x 2

Impedance : Woofer - 4Ω

: Tweeter - 8Ω

Frequency Response : 40Hz-20kHz

S/N Ratio :>72dB

:≥40dB Separation

File format

support USB : MP3 Line input : AUX

Max supported

USB memory size : 32GB

BT Name · 7FR-RT4848RUCF

BT Version : v5.0

Product Dimension

 $(W \times D \times H)$: 16.2 x 18.8 x 28.8 cm

:1U


Net. weight : 5.4 ka


Package Content:

FM Antenna Cable

:2 U Speaker Remote Control :1U QR Code guide :1U Input Cable :1U

Control Panel Description:





- 1. USB Input
- 2. Headphone output
- 3. Volume knob, Press for EQ modes in BT,USB
- 4. Previous track/channel
- 5. Play/Pause, Auto scan
- 6. Next track/channel
- 7. Input source mode
- 8. Left speaker LED connector
- 9. Line Input
- 10. Left speaker output
- 11. FM Antenna
- 12. Power On/Off

Remote Control



Standby: To awake the power or enable standby mode **Numeric Pad (0-9):** To select direct tracks from / USB drive and select two digits by consecutively pressing

Vol+: To increase the volume

Prev : To select the previous tracks in BT/USB/ or channels in FM mode

Vol-: To decrease the volume

100+ : To select tracks when more than 100 tracks present in USB

Mode: Mode Selection (BT/AUX/USB/FM)

EQ: Equalizer

Play/Pause : To Play / Pause for current track, Long Press to scan all available FM channels in FM mode

scan all avallable FM channels in FM mode

Next : To select the next tracks in BT/USB or channels in FM mode

Mute To Mute / Unmute for currently playing track

General Instruction:

BT Mode:

Switch the speaker to BT mode, Scan for nearby BT devices in your device (Phone, Tablet, etc). Tap on "ZEB-BT4848RUCF" to connect.

(Press and hold the play button for 3 seconds to disconnect from existing BT connected device)

USB Mode:

Insert the USB drive to the speaker. The speaker will detect the USB and the audio files from drive will be played automatically.

FM Radio:

Switch the speaker to FM mode. In FM mode, use the "Play/Pause" button in the control panel or remote to scan for the available FM channels. Once the scanning is done, the scanned channels will begin to play. The next button or previous button can be used to change the FM channels.

(Use the provided FM antenna cable for better reception)

AUX-IN:

The speaker can be connected to any audio device using the provided RCA to 3.5mm cable. Connect the red and white RCA cable to the speaker's rear line input ports and the other end to compatible audio source. The audio from the audio source device can be heard through the speaker after changing the mode to AUX.

LED Function:

Press and hold the Input button on the control panel or the remote to activate and deactivate the LED lights on the speaker.

Headphone Output:

Connect the headphone to the 3.5mm AUX output at the back of the speaker. When the headphone is connected the Speakers will be deactivated.

ISO 9001:2015 Certified Company www.zebronics.com