

# Portable BT Speaker CONGA



**User Manual** 

www.zebronics.com

Thank you for purchasing **ZEB-CONGA** (Portable BT Speaker). Please read this user manual carefully before operation & save this user manual for further reference.

#### Note:

- Avoid the usage of this product at the high temperature and high humidity environment
- Avoid the self-disassembly of the products or it results in voiding the product's Warranty.
- Avoid using the speaker while charging.

To know more about Terms and conditions for warranty policy, please visit

https://zebronics.com/pages/warranty-policy

#### Features:

Wireless BT v5.0 / USB / mSD / FM / AUX
Media / Volume control
Call Function
Dual Drivers
Built-in Rechargeable battery
TWS Function
Fabric Finish

Model : ZEB-PSPK 27

Output Power (RMS) : 8W

BT Version : 5.0

BT Name : ZEB-CONGA

Driver Size : 5.2cm

Speaker Impedance :  $4\Omega$ 

Frequency Response : 100Hz-18kHz

S/N Ratio :≥70dB

Max Supported

USB/mSD memory size: 32GB

Supported

Audio formats : Mp3
Charging time : 4h
Playback time : 6h\*

Product Dimension

(Dia. x H) :7.5 x 16.2cm


Net. Weight : 432g

\* at 50% Volume (LED OFF)


## Package Contents

Speaker :1 U
Charging cable :1 U
OR Code Guide :1 U

## **Product Button & Port Representation:**



- 1) Volume increase / Next Track
- 2) Volume Decrease / Previous Track
- 3) Microphone
- 4) Play, Pause / Redail / Call Attend, Call reject
- 5) Mode / TWS
- 6) Power On/Off



# **Usage Instruction:**

#### **Button Functions:**

- Press and hold the Power button for 2 seconds to Power On/Off
- Short press the Play/Pause button to Play or Pause playback also to accept incoming call or End the ongoing call
- Double press the Play/Pause button to initiate Redial function
- Short press the (+) button to increase the volume
- Short press the (-) button to decrease the volume
- Press and hold the (+) button for next track
- Press and hold the (-) button for previous track
- Short press the (M) button to change the source modes
- Long press the (M) button to enable TWS function

(The above functions are common for USB & mSD)

### **BT Pairing Instructions:**

 The speaker enters BT pairing mode automatically after it's powered on or switched to BT mode

- Turn ON the BT in your mobile device settings & search for the BT name "ZEB-CONGA"
- Once the BT name is visible in your mobile settings, tap on it and click pair to connect.

#### FM Radio:

- Short press Play/Pause button to auto scan the available FM channels.
- Long press (+/-) button to change auto scanned FM stations.

## **Charging instruction:**

 Use the provided micro USB charging cable to any DC 5V rated USB output.

## **LED Functions:**

- Red light glows Charging
- · Red light turns off Fully charged
- · Blue light blinks BT discovery mode
- Blue light glows constant BT paired successfully

ISO 9001:2015 Certified Company www.zebronics.com