

# Portable BT Speaker 20



# **User Manual**

www.zebronics.com

### Dear Consumer,

Thank you for purchasing **ZEB-DELIGHT 20**Portable BT Speaker. Please read the user manual carefully before usage & save it for future reference.

#### Note:

- Avoid the usage of this product at the high temperature and high humidity environment.
- Avoid the self-disassemble of the product as it results in the failure of Warranty.
- Turn off the speaker if the speaker is not being used for a long period of time.

### **Features**

Wireless BT
Supports USB & micro SD
Built-in FM Radio
AUX Input
TWS Function
Call Function
Media / Volume control
Built-in Rechargeable battery
RGB Lights

# **Specifications**

Output Power (RMS) :10W(5W + 5W)

BT Version :5.0

Driver Size :52mm x 2

Speaker Impedance :  $3\Omega$ 

Frequency Response : 80Hz-18kHz

S/N Ratio :≥85dB

Max Supported USB &

micro SD memory size : 32GB

Supported

Audio formats : MP3
Charging time : 3H
Playback time : 5H\*

Product Dimension  $: 200 \times 67 \times 79 \text{ mm}$ 


 $(W \times D \times H)$ 

Net. Weight :457g


# **Package Contents**

Speaker : 1 unit Charging cable : 1 unit Input cable : 1 unit

# **Buttons Descriptions:**



- 1 Previous/Volume Down
- 2 Play/Pause
- 3 Next/Volume Up
- 4 Mode
- 5 Call attend / Reject
- **6** USB Port
- Micro USB/Charging Port
- 8 AUX Port
- 9 On/Off Switch
- Micro SD Slot



# Instruction for Use Button Function:

- 1. Turn the speaker On/Off using the slider power switch.
- 2. Short press the "**M**" button to switch the modes.
- 3. Long press the "+/-" buttons to increase / decrease the volume.
- 4. Short press the "+/-" buttons to change the NEXT/PREV tracks.
- 5. Single press the " to Play/Pause the track being played.
- 6. During Calls, Press the " " button to attend/end call. Long press the " " button to reject the incoming call.
- 7. Double press " S " button to redial.

## Pairing with the BT speaker:

- 1. Power ON the Speaker and you will hear the indication for the BT mode.
- 2. Switch ON BT on your phone or tablet and search for the nearby BT devices.
- 3. Search for the BT name "**ZEB-DELIGHT 20**" and tap to connect it.

### Micro SD / USB Mode:

Connect the micro SD card / USB drive to the respective ports of the **ZEB-DELIGHT 20** and the speaker will automatically start playing from the micro SD card / USB drive.

### FM Radio:

- Once the speaker is turned ON, Please switch the speaker to FM mode using the Mode button.
- Short-press "+" or "-" to change the scanned FM channels
- Long-press "+" or "-"to adjust the volume.

**Note:** Please use Aux cable as antenna for better FM signal reception.

### **AUX-In:**

Switch the speaker to AUX mode. Connect one end of the AUX cable to the speaker & connect the other end to an audio source. The songs played from the audio source can be heard through the speaker.

### TWS Function:

- Turn on two **ZEB-DELIGHT 20** speakers you want to pair.
- Long press the "Mode" button on any one speaker to activate TWS mode.
- After few seconds, both the speakers will be connected successfully.
- Now search for nearby BT device from your mobile and tap on the BT name "ZEB-DELIGHT 20" to connect.

• To exit TWS mode, long press "MODE" button again.

## Charging the Speaker:

- 1. Connect the charging cable to Micro USB port of the speaker and insert the other end into a DC 5V charging power source/adapter.
- 2. Red LED glows indicating that the battery is being charged.

# **LED Light Control**

Long press " ▶ " key to turn the LED ON /OFF.

ISO 9001:2015 Certified Company www.zebronics.com