

# Portable BT Speaker VITA BLAST



**User Manual** 

www.zebronics.com

## Dear Customer,

Thank you for purchasing **"ZEB-VITA BLAST**" BT speaker. Please read this user manual carefully before operation & save it for future reference.

#### Note:

- Avoid the usage of this product at the high temperature and high humidity environment.
- Avoid the self-disassembly of the products or it results in voiding the product's Warranty.
- Turn off the speaker when it is not in use. To know more about Terms and conditions for warranty policy, please visit:

https://zebronics.com/pages/warranty-policy

#### Features:

Wireless BT v5.1
Supports USB & mSD card
Built-in FM Radio
AUX Input
Call Function
Media / Volume control
Built-in Rechargeable battery
TWS Function
7 LED Modes
Dual passive radiators

# **Specifications:**

Output Power (RMS) : 16W (8W + 8W)

BT Version : v5.1

Driver Size : 5.2cm x 2

Impedance :  $3\Omega$ 

Frequency Response : 100Hz-18kHz

S/N Ratio : ≥70dB

Max Supported USB/mSD

memory size : 32GB (USB)

Supported Audio formats: MP3
Charging time: 4.5h
Playback time: 15h\*

Product Dimension : 40.6 x 8.5 x 7.2cm


 $(W \times D \times H)$ 

Net. Weight : 722g

# **Package Contents:**

Speaker : 1 U
Charging Cable : 1 U
QR Code Guide : 1 U

# **Button Description:**



- 1. Power / Mode Button & TWS mode
- 2. Play/Pause, Scan Button, LED Modes & LED on/off
- 3. Next / Volume+ Button
- 4. Prev. / Volume- Button
- 5. USB Port
- 6. Microphone
- 7. Type-C Charging Port
- 8. Micro SD Card Port
- 9. AUX Port

#### **Button Functions:**

- 1. Long press the MODE button to power ON/OFF the speaker. Single Press the MODE button to change the input mode of the speaker.
- 2. Long press the "+" button to change the next track or channel when in BT/USB mode or FM mode respectively. Single press the button to Increase the speaker volume.
- 3. Long press the "-" button to go to the previous track/channel in BT/USB mode or FM mode respectively. Single press the "-" button to decrease the speaker volume.
- 4. Press the Play/Pause button to Play/Pause the track being played. Single press the same button to scan for FM channels in FM mode.
- 5. During calls, press the Play/Pause button to attend/end the call. Long press the Play/Pause button to reject an incoming call.
- 6. Double tap on MODE button to activate TWS Mode
- 7. Long press Play/Pause button to change LED light modes or on/off LED lights

## Instructions for Use:

# Charging the Speaker:

- 1. Connect the Type-C USB charging cable to the Type-C charging port of the speaker and insert the other end into a USB Power source/mobile adapter.
- 2. Red LED glows constant indicating the speaker's battery is charging. The Red LED will turn off once it is fully charged.

#### Bluetooth:

- 1. Once the speaker is Powered ON it will enter into BT mode.
- 2. Switch ON BT in your phone or tablet and search for nearby BT devices.
- 3. Search for the BT name "ZEB- VITA BLAST" and tap on it to connect it.

#### Micro SD / USB mode:

Insert the Micro SD card / USB drive into the respective ports of ZEB- VITA BLAST and the speaker would automatically start playing the MP3 files from the Micro SD card/USB drive.

## **AUX-IN:**

Connect the speaker to any device using a 3.5mm to 3.5mm AUX cable. Once connected, the speaker automatically switches to AUX mode and the audio can be heard via the speaker.

## TWS (True Wireless Stereo) Function:

- Keep both speakers in BT discoverable mode.
- Double press the MODE button on either of the speakers for it to enable the TWS Mode.
- After a few seconds you will hear a notification tone on both the speakers once both are successfully paired via TWS.
- Now turn ON the phone's BT in the settings and search for "ZEB- VITA BLAST" and tap on it to pair with it.
- If you would like to disconnect the two speaker from TWS, double press Mode button.

**Note:** Requires two speakers for TWS feature

## FM Radio:

- Switch the speaker into FM mode. Single press the Play/Pause button to initiate the auto scan for available FM channels.
- Once scanning is complete, long press the + /
- button to change the channels.

ISO 9001:2015 Certified Company www.zebronics.com